

CH-L25912 Charger Data sheet

No.	Items	Specification	Notes
Input Characteristics			
1	Input Voltage	AC 110~240V, 50-60Hz	
	Max. Input Current	1.2A	
Output Characteristics			
2	Output Voltage	DC 29.4 V	
	Output Current	1.2 A	
	Power Indication	LED=Green: No Battery Connected/ Battery Fully charged LED=Red : AC Connected/ In charging	
Charging Supervision and Protection Mechanism			
3	Over Voltage Protection	Yes	
	Output Reverse Protection	Yes	
	CCCV	Yes	
Environment			
4	Operation Temperature	-10 ~+40 F	
	Operation Humidity	< 90%	
Mechanical			
5	Dimensions	4.5"L x 2.2"W x 1.4"H	
	US AC cable	1 Pcs	
	Weight	1.4 lb (635 g)	
	Output cable	2 Pin Female Universal Plug	
	Connector/Adaptor	2 Pin Female Universal to Female Alligator Clips	

Product Pictures



Charge Instruction

1. Make sure your AC supply source is 110-240V and your battery pack match with the battery requirement.
2. Connect the charger to the AC outlet. LED=Green: it means power on or no battery connected.
3. Connect DC output to battery pack terminals. LED turn into red. It means in charging.
4. When LED turns Green, the battery pack is fully charged. You can charge next battery pack or switch off the power.

Notice

1. Make sure your battery voltage match with your charger.
2. Always place the charger in well-ventilated, dry environment and indoor use only.
3. Never charge other type batteries except Li-ION/Polymer.
4. Subject to change without prior notice, please contact us for the latest information.
5. Indoor used only, never expose the charger to water such as rain and splash.
6. Make sure good ventilation is provided when charger operation. Never place the charger near radiator, heat register or similar heat source when in charging.