

Specification & Instruction of Smart Charger CH-L9VP



Feature	<ul style="list-style-type: none"> Designed for 7.4V lithium rechargeable battery with capacity $\geq 300\text{mAh}$ Input Power: 100V - 240V AC 50-60Hz Output Power: 8.4V DC, 0.3A
Output Plug	<ul style="list-style-type: none"> Large Pin: Positive, Small Pin: Negative
LED	<ul style="list-style-type: none"> LED Green - Plug in to AC power resource, no battery LED: Red - Charging LED: Green - Fully charged
Safety Protection	<ul style="list-style-type: none"> Over voltage protection Short Circuit protection Reverse protection
Dimension	<ul style="list-style-type: none"> 75mm (2-7/8") x 30mm (1-1/8") x 65mm (2-1/2")
Weight	

Caution:

- This charger is only for Indoor use
- The charger shall be placed on a fixed horizontal surface when the charger is operated
- Avoid storing or operating the charger in highly humid place or any place with inflammable good
- Do not cover the charger when the charger is operated. The ambient temperature shall not excess 40 °C
- Do not charge the battery on the list below
 Designed Battery Voltage < 7.4V, or Designed Battery Voltage > 7.4V
 Capacity < 300mAh
- Completely plug the power cord into AC power resource
 Do not expose any metal part of the power cord during operation
 Do not use your hand or any of your body to touch the metal part of the power when you connect the power to the charger
- Do not disassembly the charger any time
- AA Portable Power is not responsible for any damage caused by any misuseage

Operation Steps:

1. Connect transfer cable, if any, to the output of charger
2. Plug the power cord/plug into the AC power resource
3. Connect the battery to the transfer cable with correct polarity
Note: Do not connect battery before providing AC power on charger
4. Check the LED indicator to see the status of the charging process
5. The charging time is variable depends on the battery